

Power Distribution Unit (PDU)

NEMA & Other Plastic Housing Series

Our reliable power distribution unit is the ideal means of powering multiple loads in 19 inch rack-mount, rack enclosures, raceways, desktops, wall-mount and more. Always your best choice for distribution of alternate, sine-wave UPS and generator power, or commercially derived AC power to connected equipment.



NEMA & Other Plastic Housing Series

Safety Approval :



Feature

- ◆ AC power line surge protector. Protect high-tech electronic devices from damage caused by dangerous spikes/surges that coming from AC power line.
- ◆ EMI/FRI noise filter. Eliminate electro-magnetic & radio frequency interference. Very important for sensitive electronic devices, like computer, mobile phone...
- ◆ Equipped with circuit breaker for overload protection.

AHOKU ELECTRONIC COMPANY

5F, NO.88, Sec.1, Nei-Hu Rd., Taipei, Taiwan

TEL:886-2-27991199 FAX:886-2-27999099

Copyright © AHOKU Electronic Company. All Rights Reserved

Specification

| Model | Outlet 5-15R | Switch | Surge Protection | Indicator (Power/Surge) | Power Cord 14 AWG 5-15P | Amp Meter | Approval |
|-------------|--------------|------------|------------------|-------------------------|-------------------------|-----------|----------|
| PD-121500A0 | 12 | Pwr w/C.B. | N/A | Pwr-red | 6Ft / BLK | ✗ | cULus |
| PD-121500A1 | 12 | Pwr w/C.B. | L-N | Surge-green | 6Ft / BLK | ✗ | cULus |
| PD-121500A2 | 12 | Pwr w/C.B. | L-N-G | Surge-green | 6Ft / BLK | ✗ | cULus |
| PD-121500A3 | 12 | Pwr w/C.B. | L-N-G+NF | Surge-green | 6Ft / BLK | ✗ | cULus |

| Model | Universal Outlet | Switch | Surge Protection | Indicator (Power/Surge) | Power Cord 14AWG IEC320 C14 | Amp Meter | Approval |
|---------------|------------------|------------|------------------|-------------------------|-----------------------------|-----------|----------|
| PD-UN071000A0 | 7 | Pwr w/C.B. | N/A | Pwr-red | 6Ft / BLK | ✗ | CE EMC |
| PD-UN071000A1 | 7 | Pwr w/C.B. | L-N | Surge-green | 6Ft / BLK | ✗ | CE EMC |
| PD-UN071000A2 | 7 | Pwr w/C.B. | L-N-G | Surge-green | 6Ft / BLK | ✗ | CE EMC |
| PD-UN071000A3 | 7 | Pwr w/C.B. | L-N-G+NF | Surge-green | 6Ft / BLK | ✗ | CE EMC |

| Model | German Type Outlet | Switch | Surge Protection | Indicator (Power/Surge) | Power Cord H05VV-F 3G,1.0MMF | Circuit Breaker | Approval |
|-----------------------------|--------------------|-----------------|------------------|-------------------------|------------------------------|-----------------|----------|
| PD-G081600A0 (CA-G807A0) | 8 | Pwr w/Indicator | N/A | Pwr-red | 1M/BLK | Optional | TUV-GS |
| PD-G081600A1 (CA-G807A1) | 8 | Pwr w/Indicator | L-N | Surge-green | 1M/BLK | Optional | TUV-GS |
| PD-G081600A2 (CA-G807A2) | 8 | Pwr w/Indicator | L-N-G | Surge-green | 1M/BLK | Optional | TUV-GS |
| PD-G081600A3 (CA-G807A3) | 8 | Pwr w/Indicator | L-N-G+NF | Surge-green | 1M/BLK | Optional | TUV-GS |

| Model | French Type Outlet | Switch | Surge Protection | Indicator (Power/Surge) | Power Cord H05VV-F 3G,1.0MMF | Circuit Breaker | Approval |
|-----------------------------|--------------------|-----------------|------------------|-------------------------|------------------------------|-----------------|----------|
| PD-F081600A0 (CA-F807A0) | 8 | Pwr w/Indicator | N/A | Pwr-red | 1M/BLK | Optional | CE |
| PD-F081600A1 (CA-F807A1) | 8 | Pwr w/Indicator | L-N | Surge-green | 1M/BLK | Optional | CE |
| PD-F081600A2 (CA-F807A2) | 8 | Pwr w/Indicator | L-N-G | Surge-green | 1M/BLK | Optional | CE |
| PD-F081600A3 (CA-F807A3) | 8 | Pwr w/Indicator | L-N-G+NF | Surge-green | 1M/BLK | Optional | CE |

| Model | Italian Type Outlet | Switch | Surge Protection | Indicator (Power/Surge) | Power Cord H05VV-F 3G,1.0MMF | Circuit Breaker | Approval |
|-----------------------------|---------------------|-----------------|------------------|-------------------------|------------------------------|-----------------|----------|
| PD-I081000A0 (CA-I807A0) | 8 | Pwr w/Indicator | N/A | Pwr-red | 1M/BLK | Optional | CE |
| PD-I081000A1 (CA-I807A1) | 8 | Pwr w/Indicator | L-N | Surge-green | 1M/BLK | Optional | CE |
| PD-I081000A2 (CA-I807A2) | 8 | Pwr w/Indicator | L-N-G | Surge-green | 1M/BLK | Optional | CE |
| PD-I081000A3 (CA-I807A3) | 8 | Pwr w/Indicator | L-N-G+NF | Surge-green | 1M/BLK | Optional | CE |

AHOKU ELECTRONIC COMPANY

5F, NO.88, Sec.1, Nei-Hu Rd., Taipei, Taiwan

TEL:886-2-27991199 FAX:886-2-27999099

Copyright © AHOKU Electronic Company. All Rights Reserved